

APPENDIX 'A'

BRITISH 405-LINE STANDARD

The following modifications necessary for operation on the British 405-line, 50 fields/sec. scanning standard, have been carried out on some cameras.

Horizontal Scan Circuit

C59 becomes 6.8nf	±20%	125V	M669404
C60 becomes 22nf	±20%	125V	M669823
C61 becomes 33nf	±20%	125V	PR22852
C62 becomes 47nf	±20%	125V	M669809
R91 becomes 1.8kΩ	±10%		671737

When servicing, adjust Horizontal Scan Osc. coil (L4) as in Chapter IV, section 'Auxiliary Controls', using a frequency of 10.125 kc/s.